


## 433.92 MHz rolling code radio command

### The ideal solution for multi-user settings with unclonable code.



- Rolling code: the “dynamic code” technology that guarantees signal safety and secrecy.
- Transmitter to transmitter self-learning.
- Even with transponder function.
- Available in the one-channel, two-channel and four-channel versions.
- 4,294,967,896 combinations.

### Dimensions of transmitters




#### Dimensions (mm/in)

MODEL	B	H	P	Weight (g/oz)
AT01	32/1.25	68/2.67	13/0.51	16/0.56
AT02	32/1.25	68/2.67	13/0.51	16/0.56
AT04	40/1.57	85/3.34	12/0.47	22/0.77


### Limits to use

MODEL	Range (m)
AT01	50 ÷ 150 / 160 ÷ 500
AT02	50 ÷ 150 / 160 ÷ 500
AT04	50 ÷ 150 / 160 ÷ 500

### Dimensions of receivers (mm)



001RBE4RC



001RE432RC

### Technical features

Type	AT01 - AT02 - AT04
Batteries	2 X CR2016 LITHIUM
Combinations	4,294,967,896
Operating temperature (°C/°F)	-20 ÷ +55/-4 ÷ +131°C/°F
Material	ABS

# The complete range



Code	Description
<b>433.92 MHz rolling code transmitters</b>	
001AT01	One-channel rolling code transmitter. 4,294,967,896 combinations.
001AT02	Bi-channel rolling code transmitter. 4,294,967,896 combinations.
001AT04	4-channel rolling code transmitter. 4,294,967,896 combinations.
<b>433.92 MHz plug-in rolling code receiver</b>	
001AF43SR	Plug-in radio frequency card for max. 25 transmitters.
<b>433.92 MHz surface-mounted rolling code receivers</b>	
001RE432RC	Surface-mounted bi-channel receiver for max. 25 transmitters - IP54, 12 - 24 V AC - DC.
001RBE4RC	12 - 24 V AC - DC IP54 surface-mounted 4-channel receiver for max. 500 transmitters, complete with n. 1 001AT04 transmitter (master).
<b>Accessories for: 001AT01 - 001AT02 - 001AT04</b>	
009TAG	Glass transponder bulb.
001P3V	Package of n. 2 3 V DC type CR2016 lithium batteries.
<b>Accessories for receivers</b>	
001TOP-A433N	Antenna.
001TOP-RG58	Antenna cable.

