

Touch

23


40.695 MHz radio command

The ideal solution for apartment blocks



- In the 2 +2 channels or 4 + 4 channels versions.
- The group of channels in use are shown by the light signal that may be either blue or red.
- Practical, with quartz technology and multi-user function.
- Harmonised frequency and ergonomic keys.
- 16,777,216 combinations.

Dimensions of transmitters




Dimensions (mm/in)

MODEL	B	H	P	Weight (g/oz)
TCH-4024	40/1.57	86/3.38	17/0.66	45/1.58
TCH-4048	40/1.57	86/3.38	17/0.66	45/1.58


Limits to use

MODEL	Range (m)
TCH-4024	50 ÷ 150 / 160 ÷ 500
TCH-4048	50 ÷ 150 / 160 ÷ 500

Dimensions of receivers (mm)



001RBE4N
001RBE42



001RE402

Technical features

Type	TCH-4024 - TCH-4048
Batteries	1 x 12 V AAA
Combinations	16,777,216
Operating temperature (°C/°F)	-20 ÷ +55/-4 ÷ +131°C/°F
Material	Polycarbonate - Rubber

The complete range



Code	Description
40.685 MHz transmitters	
001TCH-4024	2 + 2 channel multi-user transmitter. 16,777,216 combinations with self-learning function.
001TCH-4048	4 + 4 channel multi-user transmitter. 16,777,216 combinations with self-learning function.
40,685 MHz plug-in receivers	
001AF40	Plug-in radio frequency card.
40,685 MHz surface-mounted receivers	
001RE402	12 - 24 V AC - DC IP54 surface-mounted bi-channel receiver.
001RBE42	230 V AC IP54 surface-mounted 4-channel radio module.
12 - 24 V AC - DC surface-mounted radio module	
001RBE4N	12 - 24 V AC - DC IP54 surface-mounted 4-channel multi-user radio module.
Accessories for: 001TCH-4024 - 001TCH-4048	
009TAG	Glass transponder bulb.
Accessories for receivers	
001TOP-A40	Antenna.
001TOP-RG58	Antenna cable.

